## A-C010 / A-C010T Fingerprint Time Attendance



- 1. Standalone fingerprint time clock.
- 2. Fast speed for verification(Up to 200MHz CPU CLK and 100MHz system operating frequency.)
- 3.Support USB HOST and USB CLIENT both. A-C010T supports TCP/IP communication.
- 4. Three authentication mode: Fingerprint, RFID card(125Khz) and Password.
- <u>5. Special for A-C010T: simple design with TCP/IP function in lowest price(Best price for bulk order).</u>
- 6. Free RAMS software to manage employee info and attendance records. Free for updated to the latest version on website.

## **Technical Specifications:**

| Model                              | A-C010  | A-C010T     |
|------------------------------------|---|-------------|
| Real-time monitoring               | Device Pushes real-time attendance record to the RAMS Software automatically              |             |
| LCD Screen                         | 2.8 inch TFT Color Screen   |             |
| Fingerprint Sensor                 | 500DPI  |             |
| CPU                                | Up to 200MHz CPU CLK and 100MHz system operating frequency makes faster recognition speed |             |
| User Capacity                      | 2,000   |             |
| Records Capacity                   | 100,000   |             |
| Communication                      | USB   | USB, TCP/IP |
| USB Flash Drive<br>Upload/Download | Available   |             |
| Authentication Method              | Fingerprint / RFID Card(125Khz) / Password  |             |

| Proximity Card      | RFID card(125Khz, EM4100)                      |  |
|---------------------|--|--|
| Identification Time | ≤0.8 Second                                    |  |
| FRR                 | ≤0.1%  |  |
| FAR                 | ≤0.0001%                                       |  |
| Operating Mode      | Off-line/Online                                |  |
| Authentication Mode | 1:1, 1:N                                       |  |
| Language            | English  |  |
| Voice Prompt        | English  |  |
| Bell                | Built-in Timing Bell                           |  |
| Power Adapter       | DC 12V/0.5A                                    |  |
| Terminal            | $180(L) \times 134(W) \times 36(H) \text{ mm}$ |  |

IBC is your wise choice to guarantee a successful biometric solution.

www.ibcegypt.com